

# DFST Example Programme

## 2 on/off periods

Period 1: 07:00 - 08:00

Period 2: 16:00 - 18:00

### Setting a program

#### First on/off time

1. Press the Set button twice to enter the programming setting mode.
2. Press the Set button to confirm (program 01 ON, hours will flash).
3. Use the + or - button to adjust the hours (set value to **7**) and press Set to confirm, (minutes will flash).
4. Use the + or - button to adjust the minutes (set value to **00**) and press Set to confirm, (days will flash).
5. Set day combination block by pressing the + or - buttons. (set to **Monday to Sunday**)
6. Press the Set button to confirm.
7. Press the + button, this will select the program 01 OFF, press Set to confirm.
8. Use the + or - button to adjust the hours (set value to **8**) and press Set to confirm, (minutes will flash).
9. Use the + or - button to adjust the minutes (set value to **00**) and press Set to confirm, (days will flash).
10. Set day combination block by pressing the + or - buttons. (set to **Monday to Sunday**)
11. Press the Set button to confirm.

#### Second on/off time

2. Press the Set button to confirm (program 02 ON, hours will flash).
3. Use the + or - button to adjust the hours (set value to **16**) and press Set to confirm, (minutes will flash).
4. Use the + or - button to adjust the minutes (set value to **00**) and press Set to confirm, (days will flash).
5. Set day combination block by pressing the + or - buttons. (set to **Monday to Sunday**)
6. Press the Set button to confirm.
7. Press the + button, this will select the program 02 OFF, press Set to confirm.
8. Use the + or - button to adjust the hours (set value to **18**) and press Set to confirm, (minutes will flash).
9. Use the + or - button to adjust the minutes (set value to **00**) and press Set to confirm, (days will flash).
10. Set day combination block by pressing the + or - buttons. (set to **Monday to Sunday**)
11. Press the Set button to confirm.